



## A.H. Systems, Inc.

9710 Cozycroft Ave.  
Chatsworth, CA 91311



Tel: (818) 998-0223



sales@AHSystems.com

Fax: (818) 998-6892



www.AHSystems.com

## BCP-619

**Current Probe**  
100 Hz – 100 MHz

This current probe measures high power pulse currents such as those associated with EMP wave shapes. It clamps around large conductors or bundles of wire and has an aperture of 2.7".



Frequency Range: 100 Hz - 100 MHz  
Transfer Impedance (dBΩ) -90 to -43  
Max Primary Current CW 60 Amps  
Max Primary Current  
(at 400 Hz) 300 Amps  
Max Primary Current Peak 5,000 Amps  
Connector: N-Type, Female

### Physical Dimensions

Aperture: 2.7" (70 mm)  
Diameter: 5.0" (125 mm)  
Weight: 2.5 lb.'s (1.13 kg)

### Features

- High current conducted emissions measurements without saturation.
- Ideally suited to measuring currents on large cables.
- Individually Calibrated (Transfer Impedance calibration included)
- Split Type Clamp-on Design
- Three Year Warranty

Conducted currents can be measured without making direct contact with the source conductor or metallic surface by means of clamp-on current probes. The BCP-619 Current Probe is designed to permit field intensity meters, spectrum analyzers, and other 50 ohm impedance instruments to measure quantitative magnitudes of current. Measurements can be made on single and multi-conductor cables, ground and bonding straps, shielded conduits and on coaxial cables.

### Recommended Accessories

- CPF-633 Current Probe Fixture
- SAC-211 N/N Cable, 3 Meter



**A.H. Systems, Inc.**

9710 Cozycroft Ave.  
Chatsworth, CA 91311



Tel: (818) 998-0223  
Fax: (818) 998-6892

◆ sales@AHSystems.com  
◆ www.AHSystems.com



**A.H. Systems, inc.**

9710 Cozycroft Ave.  
Chatsworth, CA 91311  
818.998.0223 fax 818.998.6892  
sales@AHSystems.com www.AHSystems.com



**Broadband Current Probe  
Calibration Model: BCP-619**

Transfer Impedance Conversion Formula:

$$\text{dB}\mu\text{A} = \text{dB}\mu\text{V} - \text{dB}\Omega + \text{cable loss}$$

